



NOTES :-

1. REMOVE STRAP AND CONNECT EXTENSION BELL BETWEEN TERMINALS Nos 6 & 7 ON "BELL SET No. 31" WHEN REQUIRED.
2. THE CONNECTIONS BETWEEN THE STRIP CONNECTION IN "BOX, CASH No. 12 OR No. 13" AND THE SPRING ASSEMBLY ON THE "BOX, COIN COLLECTING No. 16" SHOULD BE MADE LOCALLY.
3. WHEN THE EQUIPMENT IS FITTED IN A KIOSK OR CABINET "CORD, INST. No. 6/25 M. 30" SHOULD BE USED. THE CORD SHOULD BE PASSED THROUGH A HOLE IN THE WALLBOARD IMMEDIATELY BEHIND THE "TELE. No. 196 MINUS CORD" AND TERMINATED DIRECT ON THE CONNECTION STRIP IN THE BOX, CASH No. 12 OR 13. WHEN THE "TELE. No. 196 MINUS CORD" IS REQUIRED TO STAND ON A DESK OR TABLE (IN SUBSCRIBERS PREMISES) A "CORD, INST. No. 5/14 B BROWN 54" SHOULD BE USED AND A "STRIP, FLEX., CORD CONN. 6 TERM. L. FITTED IF NECESSARY.
4. PROVIDE, ACCORDING TO TRANSMISSION REQUIREMENTS:- (a) FOR PUBLIC CALL OFFICE CIRCUITS - CELLS LECLANCHE DR2 (2 OR 3) AND HOUSE IN BOX BATTERY LECLANCHE WK2, 2 CELL C.O. (b) FOR SUBSCRIBERS DIRECT EXCHANGE LINE - 2 OR 3 CELLS LECLANCHE WK4, WK2, OR WK1."
5. A "BACKBOARD FOR BOX, COIN COLLECTING No. 16 A" WILL BE REQUIRED WITH "BOX, COIN COLLECTING No. 16 A COMPLETE" WHEN THE LATTER IS FITTED TO A DESK OR TABLE.
6. THE MECHANICAL FEATURES OF THE "BOX, COIN COLLECTING No. 16" ARE SHOWN ON DIAGRAM EC. 1500. (N 1184).