

Electronic Modular Switching System

Panasonic

User
Mannual

Please Read this manual before using
the Electronic Modular Switching
System.

For Single line telephones

Model
KX-T206E

Single Line Telephone Features

Contents

Making Calls	3
Intercom Calling.....	3
Outward Dialling.....	3
System Speed Dialling	3
Doorphone.....	3
When a Line is Busy.....	3
Last Number Redial.....	3
Receiving Calls	4
Answer	4
Call Pickup.....	4
While Having a Conversation	4
Call Hold	4
Call Hold Retrieve.....	4
Call Transfer.....	4
While Having a Conversation (contd.).....	5
Call Waiting	5
Conference.....	5
Call Splitting	5
Paging Features	6
Paging All Extensions	6
Paging Answer	6
Paging and transfer.....	6
Other Features	6
Intercom Alerting Mode.....	6
Other Features (contd.).....	7
Call forwarding.....	7
Call Pickup Deny.....	7
Do Not Disturb (DND).....	7
Other Features (contd.).....	8
Data Line Security.....	8
Pulse to tone conversion.....	8
Station Feature Clear.....	8
Other Features (contd.).....	9
Time Setting (extension 21 only).....	9
Date Setting (extension 21 only).....	9
Flexible Night Service.....	9

Single Line Telephone Features


Making Calls

<NOTE>

Off-Hook: Lift the handset On-hook: Replace the handset

Intercom Calling

Allows you to call another extension




The diagram shows a handset icon at the top. Below it are two telephone icons. The first is labeled 'Off-hook'. The second is labeled 'Dial extension number (21 through 26)' and has a hand pointing to its keypad.

Doorphone

Allows you to have a conversation with a visitor at your door


To call a doorphone:



The diagram shows a handset icon at the top. Below it are three elements: a telephone icon labeled 'Off-hook', the number '31', and a handset icon labeled 'Wait for confirmation and talk'. The number '31' is the largest element in the diagram.

Outward Dialling

Allows you to make a call to an outside party



The diagram shows a handset icon at the top. Below it are two telephone icons. The first is labeled 'Off-hook'. The second is labeled 'Dial line access code and telephone number' and has a hand pointing to its keypad.

To unlock the door:




The diagram shows a handset icon at the top. Below it are three elements: a telephone icon labeled 'Off-hook', the number '32', and another telephone icon labeled 'On-hook'. The number '32' is the largest element in the diagram.

System Speed Dialling


Allows you to make outside calls using previously programmed speed dial numbers.

This system supports forty speed dial numbers which are available to all extension users

To unlock the door while talking to the doorphone:



The diagram shows a telephone icon with a hand pointing to its keypad, labeled 'Press RECALL'. To its right is the number '3', labeled 'Dial 3'. The number '3' is the largest element in the diagram.




The diagram shows a handset icon at the top. Below it are three elements: a telephone icon labeled 'Off-hook', an asterisk symbol labeled 'Press *', and a telephone icon with a hand pointing to its keypad labeled 'Dial System Speed Dial number (00 through 39)'.

When a Line is Busy

Last Number Redial

Allows you to automatically re-dial the last outside number dialed.



The diagram shows a handset icon at the top. Below it are two elements: a telephone icon labeled 'Off-hook' and the number '80' labeled 'Dial 80'. The number '80' is the largest element in the diagram.

Single Line Telephone Features

Receiving Calls

Answer



Call Pickup



While Having a Conversation

Call Hold

Allows you to place an intercom or outside call on hold.

To place a call on hold:




- Depending on the system programming you may need to dial 6 after pressing the recall button. For programming, see page 28 of the installation manual.

To retrieve a call on hold:



Call Hold Retrieve

Allows you to receive a call that has been placed on hold by another extension.




- You can dial the extension number (21 through 26) which held the call or the line number.


Call Transfer

Allows you to perform a screened or Unscreened call transfer to another extension.


To perform a screened call transfer:



To perform an unscreened call transfer:



To retrieve the call when the transferred call is not answered within 30 seconds an the call has returned to you:



- For programming the hold recall time, see page 28 of the Installation Manual.

Single Line Telephone Features

While Having a Conversation (contd.)

Call Waiting

During a conversation, a call waiting tone signals that there is a call waiting. You can respond to the waiting call by disconnecting from the first call or by placing the first call on hold.

To talk to the new party by terminating the current call:




To talk to the new party holding the current call:



Conference

Allows you to add a third party to a two-party conversation and make a three party conference. You can have the following combination of calls on the line: three extensions, two extensions and one line, or one extension and two lines.

To establish a conference:



To leave the conference:




- The other two parties can continue their conversation provided they are not both lines.

To hold one party and talk to the other:



Call Splitting

Allows you to have two callers on a line and alternate between them. You can place the current call on hold and have a conversation with the other party.



- Pressing RECALL alternates between the callers.
- When you go on-hook, the other two parties callers remain on-line.


Single Line Telephone Features

Paging Features

The Paging features allow you to make a voice announcement to several persons at the same time. Your message is announced over the built-in speaker of proprietary telephones. The paged person can answer your page from a nearby telephone.


Paging All Extensions

Allows you to make a voice announcement to all extensions. Your message is announced over the built-in speaker of the proprietary telephones.




Paging Answer

Allows you to answer an announcement page at any extension within the system.



Paging and transfer


Allows you to transfer a call using the Paging to Extension feature.



Other Features

Intercom Alerting Mode

Allows you to switch voice calling to ring calling when making an intercom call. In Voice-Calling mode, you can talk to the other party immediately after the confirmation tone.



• For programming, see page 28 of the Installation Manual.


Single Line Telephone Features

Other Features (contd.)

Call forwarding

You can redirect all of your calls to another extension.


To set:



Off-hook Dial 7 Dial extension number
(21 through 26)

Dial # On-hook

To cancel:




Off-hook Dial 70# On-hook

- You may dial “0” instead of “#”

Call Pickup Deny

Allows you to prevent another extension from picking up your calls with the “Call Pickup” feature.

To set:



Off-hook Dial 731# On-hook

To cancel:



Off-hook Dial 730# On-hook

- You may dial “0” instead of “#”

Do Not Disturb (DND)

Allows you to prevent other parties from disturbing you. Your extension will not receive intercom or outside calls

To set:



Off-hook Dial 720# On-hook

To cancel:



Off-hook Dial 70# On-hook

- You may dial “0” instead of “#”.


Single Line Telephone Features

Other Features (contd.)

Data Line Security

Your extension is protected against interruptions from "Call Waiting", "Hold Alarm", and "Executive Busy Override" features. Data communication devices, such as computers and facsimiles will operate as usual.

To set the data line security feature:



To cancel the feature:




- You may dial "0" instead of "#".

External Feature Access

Allows you to access special features (e.g. Call Waiting) offered by a host PBX or Local Exchange. This feature is effective only during an outside call.

To access an external feature (e.g. Call Waiting):




- If the Exchange Line Access Number Selection is assigned as "9", the external features access number becomes "9". For programming see page 26 of the installation manual.

Pulse to tone conversion

Allows you to change from Pulse to Tone dialling so that you can access special services such as Computer based banking services.

To set:



Station Feature Clear

Allows you to reset the following station features to the default setting:

- Call Forwarding
- Data Line Security
- Call Pickup Deny
- Do Not Disturb

To clear the setting:



- You may dial "0" instead of "#"

Single Line Telephone Features

Other Features (contd.)

Time Setting (extension 21 only)

Sets the correct time.

Off-hook Dial 77 Enter hour
(01 through 12)

Enter minute Dial 0 (AM)
or 1 (PM) Dial #

- The clock starts immediately after pressing #.

Date Setting (extension 21 only)

Sets the current date.

Off-hook Dial 76 Enter year
(2 digits)

Enter month Enter day Enter day of
(01 through 12) (01 through 31) the week (1 (Sun.)
through 7 (Sat.))

Dial #

Flexible Night Service

(extension 21 only)

This system supports both DAY and NIGHT modes of operation. The system operation for originating and receiving calls can be different in night and day modes.

To set the night mode:

Off-hook Dial 782# On-hook

To return to day mode:

Off-hook Dial 781# On-hook

Single Line Telephone Features

Feature	Number
Call Forward Set/Cancel	7 (extension number) # / 70#
Call Hold retrieve	5 (Line or Extension number)
Call Pickup	40
Call Pickup Deny Set/Cancel	731# / 730#
Conference	3
Data Line Security Set/Cancel	741# / 740#
Date Setting	76 Year Month Day Day-of-the-week #
Do Not Disturb Set/Cancel	720# / 70#
Doorphone Calling/Unlock	31 / 32
/Unlock during conversation	3
Extension Calling	21 through 26
Flexible night service Set/Cancel	782# / 781#
Intercom Alerting Mode	*
Last Number Redial	80
Line access, Automatic	9 or 0 (depending upon system program)
Line access, Individual	81 or 82
Paging All Extensions	33
Paging Answer	43
Station Feature Clear	79#
System Speed Dialling	*00 through *79
Time setting	77 Hour Minute 0(AM)/1(PM) #32

Note

- you can enter “0” instead of “#” except with Date Setting, Flexible Night Service and Time Setting.

Single Line Telephone Features

Panasonic Business Systems U.K.
Panasonic House, Willoughby Road, Bracknell,
Berkshire RG12 4FP

Produced by Paul White

KX-T206E/SLT